



**Pentagon**  
Tech Fusion Services Pvt. Ltd.



**GeM**  
Government  
e Marketplace

# Pentagon Power Amplifier



**P-USB-600**

**P-USB-1100**

**P-USB-1200**

Model	P-USB-600	P-USB-1100	P-USB-1200	P-USB-1600	P-USB-3000
<b>Power Output</b>	60W RMS (80W max)	110W RMS (150W max)	120W RMS (150W max)	160W RMS (225W max)	300W RMS (375W max)
<b>Input Channels</b>	3 MIC, 2 AUX	5 MIC, 3 AUX, 1 Line in	5 MIC, 3 AUX, 1 Line in	5 MIC, 3 AUX, 1 Line in	6 MIC, 3 AUX, 1 Line in
<b>Digital Player</b>	MP3 Player with USB, SD, MMC Card Reader, FM Tuner and Bluetooth				
<b>Tone Control</b>	Bass: 10dB at 100Hz   Mid: 10dB at 1KHz   Treble: 10dB at 10KHz				
<b>Output</b>	1V Line out	1V Line out	1V Line out	1V Line out	200mV Pre out, 1V Line out
<b>Speaker Output</b>	4Ω, 8Ω, 70V, 100V	4Ω, 8Ω, 70V, 100V	4Ω, 8Ω, 70V, 100V	4Ω, 8Ω, 70V, 100V	4Ω, 8Ω, 70V, 100V
<b>Frequency Response</b>	50 Hz - 15.7 KHz	50 Hz - 15 KHz	50 Hz - 15 KHz	50 Hz - 15 KHz	50 Hz - 15.7 KHz
<b>S/N Ratio</b>	65 dB	62 dB	62 dB	62 dB	65 dB
<b>Power Supply</b>	AC 230V/50Hz, DC 12V	AC 230V/50Hz, DC 24V	AC 230V/50Hz, DC 12V	AC 230V/50Hz, DC 24V	AC 230V/50Hz, DC 24V
<b>Dimensions</b>	W425xH100xD30 0mm	W410xH140xD32 0mm	W410xH140xD32 0mm	W410xH140xD3 20mm	W505xH155xD3 40mm
<b>Weight</b>	7.6 Kgs	9.5 Kgs	9.5 Kgs	14 Kgs	17.5 Kgs



**P-USB-1600**



**P-USB-3000**

**PENTAGON TECH FUSION SERVICES PVT LTD**

A-80, 3<sup>rd</sup> Floor, DDA Commercial Complex, Okhla Industrial Area, Phase 2  
New Delhi - 110020

+91 - 11 - 46561005

+91 - 9599599041 / 42

+91 - 8076924850

✉ info@pentagontech.in

☎ 1800 572 5949

🌐 www.pentagontech.in



**Pentagon**